

IUW upgrading instruction


一、 Setup environment

Please use WINDOWS XP/WINDOWS 7 system and install [dotnetfx.exe](#) & [vcredist_x86.exe](#) under IUW folder (network should be connected). Use the right computer till it can run IUW tool well.

二、 Burning Micro SD card steps.


A. Import the right firmware into Micro SD card.

1. Use card reader to connect the Micro SD card with PC.
2. Run IUW.EXE
3. click [File](#)—>[New](#)—>[New IUS](#) button.




4. For IUS template, select: [android: nand](#), For Image folder, select the [right firmware path](#). Then click [Wrap](#) to start import right firmware to Micro SD card.

Select :
android
nanad



Then click


Import End, see below image.




B、 Format Micro SD card


1. Import end, click **Disk ---Normalize Disk---**Mass storage Device USB

Device---Normaliz**---**continue—OK, as below illustration.







Format end, see below image.



C. Burning the upgrading firmware into Micro SD card.


Click: . Disk---Make Burn Disk---Mass storage Device USB Disk---Make---Continue---Make

Burn disk Success ---OK See below illustration:



Click
"OK"

Burn end, see below image:



4. Finish above steps. Take off the Micro SD card.

二. Using this Micro SD card for upgrading.

1. Power off the device, and insert the Micro SD card. Then press on the power key for 3 second and release. Wait for few seconds, the screen light on. Staring upgrading. (Make sure the device battery is more than 50%, if not, please charging during the upgrading)

2. Till the screen show: **Remove Sdcard and reboot**, take off the Micro SD card. The device will be re-power up automatically. (If not, please press on power key for 3seconds to repower up the device.). Upgrading finished. See below



image.

Show : Remove sdcard and
reboot