How to get camera ID code / Jak zjistit ID kód kamery

iGET SECURITY M3P15v2, EP15, M3P18v2, EP18, M3P20v2, EP20

1) EN: Search " CamHipro" app from APP Store or Play Store in your smartphone and install it.

CZ: Vyhledejte aplikaci "CamHipro" na iOS APP Store nebo Google Play Store ve vašem telefonu a nainstalujte ji.

2) EN: Click the button "Click add device", choose the "IP camera", then click "New device".

**Power On camera, wait 2 minutes, please press and hold the reset button on the back of the device 30 seconds.

CZ: Klikněte na tlačítko "Click add device", zvolte "IP camera", poté klikněte na "New device".

**Zapněte kameru do napájení , vyčkejte 2 minuty, prosím stiskněte a držte resetovací tlačítko na zadní straně kamery 30 vteřin.

China Mobile "ll 🕿 🚍 🔍	■ ② 稔 () 16:50	00 ← 0	0. 0. 🗆			$\leftarrow \rightarrow$	Q. Q.		*
Camera		China Mobile 🗐 🗟	() 🗖 🚬	■ ② 攻 回 # 18	8:30 Ch	hina Mobile "سالماً م	R 🔁 🔍		80 16:51
Click Add device		IP camera Battery wireless 4G camera Add a sharing de	Camera camera rvice Cancel		>	Devices not fi In-use dev	Add device New device connected to the strues or factory Device in the the LAN / Inter-	e ce ne network a r reset ise n connected net afersales50	fter to

3) EN: After reset please wait 2 minutes, and click on button "Power is on, next step".

CZ: Po resetování kamery vyčkejte 2 minuty, poté klikněte na "Power is on, next step".



4. EN: Please click "Not connected to the network cable"

CZ: Prosím klikněte na "Not connected to the network cable".



5. EN: Please choose "AP distribution network equipment".

CZ: Prosím zvolte "AP distribution network equipment".



6. EN: There will be 4 steps of connecting your phone's wireless network to your device hotspot. You can swipe this interface to view all the tips. Then go to the next step by click "Go to settings".

CZ: Následují 4 kroky pro připojení vašeho telefonu k WiFi hotspot síti kamery. Zkontrolujte dle obr. níže tipy a klikněte na "Go to settings".

	L ~ ~ ···	China Mobile 🗐 🗟 🧰 🤰	Im № 901+ 10:26	China Mobile 🗐 🗟 🚾 🚴	國 论 [90]++10:26	China Mobile 📶 🗟 🧰 💄	10 🖄 90 I
Add way	× (20) 14 18:37	< Ad	d way \times	< Add wa	iy X	< Add way	1
ease connect your phone's network to your device ho 1. Open Settings -> Select WL/	wireless tspot N	Please connect yo network to you 2. Select "IPCAM-XX	our phone's wireless Ir device hotspot XXXX [®] device hotspot	Please connect your network to your do 3. Connect hotspot, default p	phone's wireless evice hotspot bassword: '01234567'	Please connect your p network to your de 4. After the connection is su CamHipro	hone's wire vice hotspo ccessful, return
No SMD 9: 38.8K/s † do (01.31.) Settings	14:50 No 55	No SIMD 〒 3.26K/s ∲	88100 (100)+1510 :	No SIM® € 18.0K/s ∲	86 (D) (300 + 15:10 No 58 15	No SIMD 帝 69.38/8 中	@Q(20+1511
SUGGESTED FEATURES	← ₩L30	WLAN HICHIP	• •	C 01234567		WLAN AVAILABLE NETWORKS	
Wireless & networks WLAN, Dual SIM settings, Mobile network	> HCH Served.	PCAM-800020 Saved, encrypted (no Internet	200856)	9 90	Avial. IPCAI Centre	IPCAM-800020 Connected (no internet access) HICHIP_5G	6
Device connectivity Bluetooth, NFC, Printing	> China Encrys China	ChinaNet-aFi3 Encrypted (WPS available) ChinaNet-MeQd	ର	5 5	HICH Savid MERC Savid	Saved, encrypted (good quality) MERCURY_5G_72C2 Saved, encrypted (available)	<u></u>
Magstine anlock, Themes Display Brightness, Eye comfort, Text and display size	> Cu75 frons > CULK	CU701 Encrypted (WPS available)	~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~	3	MER Served HICH	MERCURY_72C2 Saved, encrypted (available)	<u></u>
Sounds Do not disturb, Ringtone, Vibrate	> GZYB Encryp	CU_k3yn Encrypted (WPS available)	<u>n</u>		China	HICHIP Saved, encrypted (no Internet access) ChinaNet-aFi3	
Notifications Badges, Lock screen notifications	>	GZYBJ Encrypted	R	000	0	Encrypted (WPS available)	2
Go to settings		Go to		Go to sett			

7. EN: For Android phones, it will automatically jump to the interface of network settings. Please choose the "IPCAM-*****" and enter the pass word "01234567". For IOS, you may need to go to the WLAN settings manually.

CZ: Pro Android telephony, aplikace vás automaticky přesune do výběru WiFi sítí. Prosím vyberte síť "IPCAM-*****" a zadejte heslo "01234567". Pro telefony iOS vstupte do nastavení WiFi sítí ručně.

	□` * …) ⊕ ⊡ □ੈ *, •••
China Mobile 🖏 🗟 🚴 🔤 🧱 🔍 …	■ 웣 ⑧0+∮10:09	China Mobile "내 (중 🚬 💩 🚾 🗽 🖤 🛛 🖾 政 💷) 🕫 10:10 China Mobile "내 🤿	№ 段 📧 🕴 10:13
← WLAN	::	\leftarrow IPCAM-050781 \leftarrow WLAN	::
WLAN		01234567 ④ WLAN	
		Show advanced options	RKS
H3C_028579_WIFI5_5G Encrypted		IPCAM-050781 Connected (no Interne	rt access)
IPCAM-050781 Encrypted	<u></u>	CANCEL CONNECT dinsafersales50 Saved, encrypted (goo	nd quality)
ldgame Encrypted (WPS available)		Secure input	ible)
seaquant Encrypted	ŝ.	1 2 3 4 5 6 7 8 9 0 Encrypted	<u></u>
seaquant_5G Encrypted	ŝ.	q w e r t y u i o p Encrypted (WPS availa	ible)
TP-LINK_3442 Encrypted		a s d f g h j k l dinsafersales24 Encrypted	
DIRECT-DA-HP Laser 178nw Encrypted	Ĩ	Triangle Triangle Triangle Direct-cb-HP D Encrypted (WPS availation of the second of	eskJet 2600 series 🕋
Thinkvision_D39284	(direct-da-HP La	ıser 178nw 👝

8. EN: Go back to the interface of "CamHipro" APP. It will automatically jump to the following interface, please click "YES, I WANT TO ADD DEVICE" and show us the picture as below (especially UID), we will generate a new QR code to you.

CZ: Nyní se vraťte zpět do aplikace "CamHiPro". Automaticky se zobrazí rozhraní viz obr. níže, klikněte na "YES, I WANT TO ADD DEVICE", a vytvořte printscreen obrazovky nebo opište kód UID a zašlete jej na technickou podporu značky iGET. Technici pro vás vygenerují nový QR kód.

China Mobile ⁴ , ଣା ବି	4 China Mobile ⁴ , all 🛜 🔤 🕸 🚳 ↓ 10:14
AP equipment ×	< Device information ×
The current camera is detected as the AP hotspot mode	Fill in your device information
The hotspot device UID has been found:	UID: FDTAA-050781-XVHCH
	Username:
FDTAA-050781-XVHCH	Password:
YES, I WANT TO ADD THIS DEVICE	
	ADD TO