Návod na aktualizaci hodinek CZ iGET FIT F20 a F25

Videonávod najdete zde: <u>https://youtu.be/X6V1PJGlzIM</u> Videonávod pouze pro hodinky iGET FIT F20 a F25 najdete zde: <u>https://youtu.be/pFS-0rfvqK0</u>

Z produktových stránek si stáhněte do vašeho telefonu aplikaci OTA, povolte instalaci z vnějších zdrojů a nainstalujte ji.

https://www.iget.eu/sites/data/nositelnosti/app/ota/ota.apk

Z produktových stránek si stáhněte do vašeho telefonu ZIP soubor s aktualizačními soubory. Příklad pro hodinky iGET FIT F20 Black:

Dostupné nové verze FW:

Popis	Datum uvolnění	Velikost	Stažení
Ruční aktualizace zařízení - návod + video provedení aktualizace	12.11.2020	1 MB	
Aplikace OTA pro aktualizaci	12.11.2020	4.1 MB	8
FW pro zařízení 1.0.5 (+ měření O2 a tlaku krve)	23.02.2021	700 KB	
FW pro zařízení 1.0.1	12.11.2020	700 KB	
Aplikace iGET FIT Android - stabilní 1.0.0.17	05.04.2021	90 MB	-

Z Google Play si stáhněte aplikaci aplikace WinZip – Zip UnZip Tool:

https://play.google.com/store/apps/details?id=com.winzip.android

Stažené ZIP soubory rozbalte pomocí aplikace **WinZip – Zip UnZip Tool** do přímo do nové složky nebo do složky Download. Důležité je vědět, kde jsou rozbalené soubory uložené!



Odkazy na produktové stránky: http://www.iget.eu/cs/fit-f20-black http://www.iget.eu/cs/fit-f25-black

Aktualizace pomocí aplikace OTA

- Zapněte Bluetooth telefonu a zkontrolujte, zda hodinky máte odpárované z aplikace iGET FIT či iGET GO a také z <u>Bluetooth v nastavení telefonu</u> (správně by tam to nemělo být vůbec - NIKDY).
- 2. Otevřete aplikaci OTA.
- 3. Vyberte možnost HID.



4. Kontrola nastavení aplikace

Klikněte na tlačítko SETTINGS a nastavte DFU CONFIGURE a DFU CONFIGURE OPTIONS dle obrázků.

14:19 🖬 🧃 🗢 🗹	≭ 🛜 ็แI 🛙 26 %	11:16 🗢 🗅	Soul 🗎	11:17 🗢 🖪	Stat 🖬
← HID OTA Over BLE	SETTINGS	← Settings		← Settings	
		CONFIGURE D G	АТТ	DFU juke CONFIGURE inhermutic is.	GATT
		Battery		DFU Configure Developer Options	
	-	Battery Check Low Battery Warning	۲	Breakpoint Resume Retransfer from the received image offset during the last connection	•
Device	No Device 💙	Low Battery Threshold 30%		Chip Type Check OFF	۲
Work Mode	>	Image Version		Image Section Size Check	
File Path	No File 📏	Image Version Check Do not check the firmware version, all files will be upgraded.	۲	No Image Size and Section Size Check Active and Reset Command Ack	
		Version Check Mode STRICT	Π	OFF Disconnect connection when ota failed ON	
		DFU Configure File Suffix bin		Remove Bond OFF	۲
		Automatic Active Image		HID Device OFF	۲
	•	automatically active image after the upgrade is successful		Max Reconnect Times	
				Throughput	-
		III O <		III O <	

5. Aktualizace se skládá ze dvou kroků nebo ze tří kroků pro modely F20 a F25.

a) Aktualizace UI (User Interface)

klikněte na položku Device a v seznamu dostupných zařízení (Available Devices) dle názvu (jako první písmeno se může objevovat H) najděte svůj typ zařízení a ověřte si, že sedí i MAC adresa (MAC adresu zjistíte v hodinkách v menu Nastavení).

14:19 🖬 🧃 🗘 🗹	≭ ि्*all 🛿 26 %	12:26 🧃 🤫	9.00 🔞 🖓 🖌 75 % 🗎
← HID OTA Over BLE	SETTINGS	← Scanner	C STOP :
		Bondeded Devices	
		ElePods 41:42:60:5E:6D:8F	
	-	Parrot CK3100 00:12:1C:24:9E:A7	
		SONY:GTK-X1BT D8:5D:E2:77:37:8C	
Device	No Device 📏	Available Devices	
Work Mode	>	HiGET F2X-C1D A5:2A:21:B0:0C:1D	(;
File Path	No File 📏	FIT F3 F1:68:20:09:12:12	¢
		HiGET F60 AB:2A:21:B0:1D:AA	¢
		H027T_T_E07 AC:2A:21:B0:9E:07	÷
		FIT F3 FF:BE:6E:F2:D4:BE	•
		FIT F3 CF:63:56:63:61:A1	•
		HIGET F30 AE:2A:21:AF:93:2C	•
		X1 C0:0D:95:72:ED:F0	÷
	•	iGET F4 EA:72:DD:40:93:1D	
a 0		HUAWEI WATCH GT-284 F4:BF:80:88:42:84	

- Work Mode nastavte na Silent mode.
- File Path vyberte složku, kam jste rozbalili stažený ZIP archiv a vyberte soubor, který <u>neobsahuje</u> v názvu app_MP => 0205_HSD_FP140_02_20201201_MP-a957c66bba6e858e293965ed3a4291ce.bin.

14:19 🖬 🧃	$\phi \prec$	≭ જ્ઞ≞al i 2	6 %	14:19 🖬 🧃	φ×	≭ இ‴all ⊡ :	26
← HID OTA	Over BLE	SETTIN	IGS	← HI ot	D A Over BLE	SETTI	NG
	UPLOAD				UPLOA	D	
Device	HIGET F60 / A	B:2A:21:B0:0C:37	>	Device	HiGET F60 / A	B:2A:21:B0:0C:37	
Work Mode		Silent Mode	>	Work Mode		Silent Mode	
File Path		No File	>	File Path	0209_TB_YP130 P-b0de43b5cc0d9	_03_20200720_M 98eada42353ef98 2c581.bin	1
		-				_	

- Pokud se objeví chybová hláška Error Code:0x1003 Title: null Detail:null viz. obrázek, tak je nutné vybrat znovu soubor, který <u>neobsahuje</u> v názvu app_MP, ale jiným postupem. Vraťte se zpět na seznam souborů až na seznam rozdělení souborů, kde najděte název <u>Vašeho telefonu</u> (viz. obrázek), který vyberte, následně pokračujte do složky, kde máte rozbalený zip soubor/rozbalené soubory např. název telefonu A9 Pro -> složka Download -> složka fit f20 a f25 -> soubor pro instalaci (který <u>neobsahuje</u> v názvu app_MP).

14:19 🖬 🧃		≌,¶ † ∶	26 %			
← HID OTA		SETTI	NGS		Videa	
				±	Stahování	
			-	Ni	ázev Vašeho telefonu A9 Pro Volný prostor: 110 GB	
Device	HIGET F2X-240 / AC:4A:21	:80:02:40	>			
Work Mode	Sil	ent Mode	>	4	Disk	€
File Path	Error Cod	e: 0x1003 Title: null letail: null	>		app.igetit@gmail.com	
			_		Disk	5

 Klikněte na tlačítko UPLOAD (START) – V průběhu aktualizace se nevzdalujte s hodinkami od mobilního telefonu a pokud možno snažte se udržet obrazovku telefonu aktivní občasným kliknutím na displej telefonu, aby nedošlo k zavření aplikace v průběhu přenosu. Vyčkejte, na dokončení aktualizace – cca 3-4 minut.

Po skončení aktualizace (dosažení 100%) se vraťte zpět na úvodní obrazovku a opět vyberte HID.

b) Aktualizace samotného firmwaru hodinek

klikněte na položku Device a v seznamu dostupných zařízení (Available Devices) dle názvu (jako první písmeno se může objevovat H) najděte svůj typ zařízení a ověřte si, že sedí i MAC adresa (MAC adresu zjistíte v hodinkách v menu Nastavení)

14:19 🖪 🧃 🗘 🗹	≭ 🛜 [#] all 🛿 26 %	12:26 🧃 🥴	0.00 🗇 🗳 🚄 7
← HID OTA Over BLE	SETTINGS	← Scanner	
		Bondeded Devices	
		ElePods 41:42:60:5E:6D:8F	
	-	Parrot CK3100 00:12:1C:24:9E:A7	
		SONY:GTK-X1BT D8:5D:E2:77:37:BC	
Device	No Device >	Available Devices	
Vork Mode	>	HiGET F2X-C1D A5:2A:21:80:0C:1D	
ile Path	No File 📏	FIT F3 F1:68:20:09:12:12	
		HIGET F60 AB:2A:21:B0:1D:AA	
		H027T_T_E07 AC:2A:21:B0:9E:07	
		FIT F3 FF:BE:6E:F2:D4:BE	
		FIT F3 CF:63:56:63:61:A1	
		HIGET F30 AE:2A:21:AF:93:2C	
		X1 C0:0D:95:72:ED:F0	
	•	iGET F4 EA:72:DD:40:93:1D	
1		HUAWEI WATCH GT-284	

- Work Mode nastavte na Normal mode
- File Path vyberte složku, kam jste rozbalili stažený ZIP archiv a vyberte soubor, který <u>obsahuje</u> v názvu app_MP => app_MP_unknown#_1.0.4.0_ec009ca2-655fb89610e0aef0a1afb5637fa434bc.bin. Opět vybírejte soubor způsobem popsaným výše.

14:19 🖬 🧃	\$ ⊻	∦ ଲି"սI 🛙 26	%	14:19 🖬 🥤	¢ ⊻	¥ ଲି"แI û 26	5 '
) A Over BLE	SETTING	GS	← HID OTA	Over BLE	SETTIN	G
Device	HiGET F60 / AB:2	A:21:B0:0C:37	>	Device	HiGET F60 / A	AB:2A:21:B0:0C:37	
Work Mode	[Normal Mode	>	Work Mode		Normal Mode	
File Path		No File	>	File Path	app_MP_unknow ca2-bba5e702b9	n#_1.0.4.0_ec009 d4c464a4a4b5cf2 75bb59e.bin	
						7500576.000	
		0					
		-				-	

 Klikněte na tlačítko UPLOAD (START) – V průběhu aktualizace se nevzdalujte s hodinkami od mobilního telefonu a pokud možno snažte se udržet obrazovku telefonu aktivní občasným kliknutím na displej telefonu, aby nedošlo k zavření aplikace v průběhu přenosu. Vyčkejte na dokončení aktualizace – cca 2-3 minuty.

14:19 🖬 🧃	ଦ ⊻	6 %	14:19 🖬 🕯	i o ⊻	≭ ⊜ ″ता û	26 %
← HIC	D SETTIN	IGS	← HI	D A Over BLE	SETTI	NGS
	UPLOAD			STOP		
		-	ota proces	sing		29%
			sending file 1	/1		2010
)evice	HiGET F60 / AB:2A:21:B0:0C:37	>	Device	HIGET E60 /	AB-2A-21-B0-0C-27	>
/ork Mode	Normal Mode	>	Device	HIGET FOOT	ND.2A.21.D0.00.37	/
ile Path	app_MP_unknown#_1.0.4.0_ec009 ca2-bba5e702b9d4c464a4a4b5cf2	>	Work Mode		Normal Mode	>
	75bb59e.bin		File Path	app_MP_unknow ca2-bba5e702b9	/n#_1.0.4.0_ec009 /d4c464a4a4b5cf2 75bb59e.bin	>
	U				-	

 V případě chybové hlášky "low image version" klikněte na SETTINGS a v záložce DFU CONFIGURE v části Image version vypněte Image Version check. Začněte znovu.

	13:42 ▣ ÕЮ⊀%	11 🙃 1 50	← Settings
÷	HID OTA Over BLE	SETTINGS	OFU DEU CONFIGURE GATT
	UPLOAD	\square	Battery Battery Check
			Low Battery Threshold
			Image Version
Device	HIGET F2X-BC1 / AD:2A:21:	AF:DB:C1	Image Version Check Low Version Warning Tohle vypnout
Work Mode	e Norn	nal Mode >	Version Check Mode
File Path	low imag	e version	STRICT
			DFU Configure

c) Aktualizace ciferníků – POUZE pro F20 a F25

Klikněte na položku **Device** a v seznamu dostupných zařízení (Available Devices) dle názvu (jako první písmeno se může objevovat H) najděte svůj typ zařízení a ověřte si, že sedí i MAC adresa (MAC adresu zjistíte v hodinkách v menu Nastavení).

14:19	⊒ <i>1</i> ◊ ⊻	≭ 🗟 "ग। 🖬 26 %	12:26 🧃 🤫
	HID OTA Over BLE	SETTINGS	← Scanner
			Bondeded Devices
			ElePods 41:42:60:5E:6D:8F
		-	Parrot CK3100 00:12:1C:24:9E:A7
			SONY:GTK-X1BT D8:5D:E2:77:37:BC
Device		No Device >	Available Devices
Work Mo	ode	>	HIGET F2X-C1D A5:2A:21:B0:0C:1D
File Path		No File	FIT F3 F1:68:20:09:12:12
			HIGET F60 AB:2A:21:B0:1D:AA
			H027T_T_E07
			FIT F3
			FIT F3
			HIGET F30
			AE:2A:21:AF:93:2C
			C0:0D:95:72:ED:F0
		U	iGET F4 EA:72:DD:40:93:1D
			HUAWEI WATCH GT-284

- Work Mode nastavte na Silent mode.
- File Path vyberte složku, kam jste rozbalili stažený ZIP archiv a vyberte soubor se jménem 026_6_04_20200519180938_MP-b08aadfa3a33d7f24d87d376198525d4.bin. Opět vybírejte soubor způsobem popsaným výše.

14:19 🖪 🧃 🗘 🗹	¥ ि्र"।।। 🛿 26 %
← HID OTA Over BLE	SETTINGS
UPLOA	D
Device HiGET F2X-1D6 /	(AB:2A:21:B0:0C:37 💙
Work Mode	Silent Mode >
File Path	No File >
	0

 Klikněte na tlačítko UPLOAD (START) – V průběhu aktualizace se nevzdalujte s hodinkami od mobilního telefonu a pokud možno snažte se udržet obrazovku telefonu aktivní občasným kliknutím na displej telefonu, aby nedošlo k zavření aplikace v průběhu přenosu. Vyčkejte, na dokončení aktualizace – cca 3-4 minut.



Po skončení aktualizace (dosažení 100%) se vraťte zpět na úvodní a aplikaci ukončete.

A máte HOTOVO. Aktualizace nemusí nutně probíhat v obou krocích, je možné, že vyjde update pouze na UI anebo jen na samotný FW hodinek.

Instructions for updating the watch iGET FIT F20 and F25

Videoguide find here: <u>https://youtu.be/X6V1PJGIzIM</u>

- Download the OTA application to your phone from the product pages, enable installation from external sources, and install it.
 - https://www.iget.eu/sites/data/nositelnosti/app/ota/ota.apk
- Download the ZIP file with update files from the product pages to your phone. For example for model iGET FIT F20 Black

Dostupné nové verze FW:

Popis	Datum uvolnění	Velikost	Stažení
Ruční aktualizace zařízení - návod + video provedení aktualizace	12.11.2020	1 MB	
Aplikace OTA pro aktualizaci	12.11.2020	4.1 MB	8
FW pro zařízení 1.0.5 (+ měření O2 a tlaku krve)	23.02.2021	700 KB	8
FW pro zařízení 1.0.1	12.11.2020	700 KB	
Aplikace iGET FIT Android - stabilní 1.0.0.17	05.04.2021	90 MB	

- Download the WinZip Zip UnZip Tool app from Google Play: https://play.google.com/store/apps/details?id=com.winzip.android
- Unzip the downloaded ZIP files to your mobile phone using the application WinZip Zip UnZip Tool.



Links to product pages: http://www.iget.eu/cs/fit-f20-black http://www.iget.eu/cs/fit-f25-black

Update using OTA APP

- 1. Turn on the phone's Bluetooth and <u>make sure your watch is paired from the iGET FIT or iGET GO</u> <u>application</u> and <u>also from Bluetooth in the phone's settings</u> (it shouldn't be there at all).
- 2. Open the OTA application.
- 3. Select HID.

14:19 🖪 🧃 🌣 🗹	≭ 😤 ିail 🖬 26 %
	Ø
HID	ø
Chips: RTK8762D	
Function Test	
Chips: 8762A/8762C/8762D/8762E/8	752C/8763B

4. Checking settings of APP

Push the button **SETTINGS** and set all **DFU CONFIGURE** and **DFU CONFIGURE OPTIONS** as on pictures.

14:19 🖪 🧃 🗘 🗹	∦ क्वि"ता û 26 %	11:16 🗢 🗅 👒	ical 💼	11:17 🜩 🖪	Seal 🗎
← HID OTA Over BLE	SETTINGS	← Settings		← Settings	
		CONFIGURE D GAT	тт	DFU DFU CONFIGURE	GATT
		Battery		DFU Configure Developer Options	
		Battery Check Low Battery Warning	•	Breakpoint Resume Retransfer from the received image offset during the last connection	
Device	No Device 📏	Low Battery Threshold 30%		Chip Type Check OFF	
Work Mode	>	Image Version		Image Section Size Check	
File Path	No File 📏	Image Version Check Do not check the firmware version, all files will		No Image Size and Section Size Check	
		be upgraded.		Active and Reset Command Ack OFF	۲
		Version Check Mode STRICT		Disconnect connection when ota failed ON	
		DFU Configure		Remove Bond	
		File Suffix bin			
		Automatic Active Image		OFF OFF	
	•	is successful		Max Reconnect Times	
				Throughput	100
				III O <	

5. The update consists of two steps and for F20 and F25 three steps.

a) User Interface update (UI)

- Click on the **Device** item and in the list of available **Devices by name** (H may appear as the first letter), find your device type and verify that the MAC address also fits (you can find the MAC address in the watch in the Settings menu).

4:19 🖬 🧃 🗢 🗹	≭ 🐨 all 🛿 26 %	12:26 🧃
HID OTA Over BLE	SETTINGS	← Scann
		Bondeded Devices
		ElePods 41:42:60:5E:6D:8F
	-	Parrot CK3100 00:12:1C:24:9E:A7
		SONY:GTK-X1BT D8:5D:E2:77:37:BC
	No Device 📏	Available Devices
de	>	HiGET F2X-C1D A5:2A:21:B0:0C:1D
h	No File 📏	FIT F3 F1:68:20:09:12:12
		HiGET F60 AB:2A:21:80:1D:AA
		H027T_T_E07 AC:2A:21:80:9E:07
		FIT F3 FF:BE:6E:F2:D4:BE
		FIT F3 CF:63:56:63:61:A1
		HIGET F30 AE:2A:21:AF:93:20
		X1 C0:0D:95:72:ED:F0
	•	iGET F4 EA:72:DD:40:93:1D
1 0		HUAWEI WATCH GT-2

- Work Mode set to Silent mode.
- File Path select the folder where you unzipped the downloaded ZIP archive and select the file that <u>does not contain</u> the app_MP name => 0205_HSD_FP140_02_20201201_MP-a957c66bba6e858e293965ed3a4291ce.bin.

:19 🖪 🧃 🤇	5 ×	¥ இ [®] all 0 2	6 %	14:19 🖪 j	i ¢ ⊻	¥ જ્વૈતા 0
HID OTA (Over BLE	SETTI	IGS	← H	I D ΓΑ Over BLE	SETT
					UPLO	AD
			-			
)evice	HIGET F60 / AE	:2A:21:80:0C:37	>	Device	HIGET F60 /	AB:2A:21:B0:0C:37
Vork Mode		Silent Mode	>	Work Mode	•	Silent Mode
File Path		No File	>	File Path	0209_TB_YP13 P-b0de43b5cc0	0_03_20200720_M d98eada42353ef98 2c581.bin
		•				•

- If the error message Error Code:0x1003 Title: null Detail:null appears, see the picture, then it is necessary to select the file again, which <u>does not contain</u> the **app_MP** in the name, but by a different procedure. Go back to the file list until you reach the file split list, where you find the name of your phone (see picture), which you select, then proceed to the folder where you have the zip file/unzipped files e.g. phone name A9 Pro -> Download folder -> fit folder f20 and f25 -> installation file (which does not contain app_MP in the name).

4:19 ■ 🧃 Φ 🗹 ← HID OTA Over BLE	≵ क्र≝ _ग ा। ⊡ 26 % SETTINGS	Videa	
		👱 Stahování	
	-	Name Yours phone A9 Pro Volný prostor: 110 GB	
ork Mode	Silent Mode	Disk	
File Path Error	r Code: 0x1003 Title: null	app.igetfit@gmail.com	≥

- Click on the UPLOAD (START) button - During the update, do not move away with the watch from the mobile phone and, if possible, try to keep the phone screen active by occasionally clicking on the phone screen to avoid closing the application during the transfer. Wait for the update to complete - about 3-4 minutes.



b) Update of the watch firmware itself

- Click on the **Device** item and in the list of available Devices by name (H may appear as the first letter) find your device type and verify that the MAC address also fits (you can find the MAC address in the watch in the Settings menu).

14:19 🖬 🧃 🗘 🗹	🗴 🤶 al 🗋 26 %	12:26 🧃 🥠
← HID OTA Over BLE	SETTINGS	← Scanner
		Bondeded Devices
		ElePods 41:42:60:5E:6D:8F
	-	Parrot CK3100 00:12:1C:24:9E:A7
		SONY:GTK-X1BT D8:5D:E2:77:37:BC
Device	No Device >	Available Devices
Work Mode	>	HiGET F2X-C1D A5:2A:21:80:0C:1D
File Path	No File 📏	FIT F3 F1:68:20:09:12:12
		HIGET F60 AB:2A:21:B0:1D:AA
		H027T_T_E07 AC:2A:21:B0:9E:07
		FIT F3 FF:BE:6E:F2:D4:BE
		FIT F3 CF:63:56:63:61:A1
		HIGET F30 AE:2A:21:AF:93:20
		X1 C0:0D:95:72:ED:F0
	•	iGET F4 F4-72-DD:40-93-1D
1 0		HUAWEI WATCH GT-284

- Work Mode set to Normal mode
- File Path select the folder where you unzipped the downloaded ZIP archive and select the file that
 <u>contains</u> the app_MP name => app_MP_unknown#_1.0.4.0_ec009ca2 655fb89610e0aef0a1afb5637fa434bc.bin. Again, select the file as described above.

14:19 🗷 🧃	ଦ⊻ ≯ ବି"ଲାପ	26 %	14:19 🖪 🖡	Φ ⊻	¥ ଲି"ul û 2	.6 %
	Over BLE	INGS) A Over BLE	SETTIN	٩GS
		-				-
Device	HiGET F60 / AB:2A:21:B0:0C:37	7 >	Device	HIGET F60 / A	B:2A:21:B0:0C:37	>
Work Mode	Normal Mode	a >	Work Mode		Normal Mode	>
File Path	No File	>	File Path	app_MP_unknow ca2-bba5e702b9	n#_1.0.4.0_ec009 d4c464a4a4b5cf2 75bb59e.bin	>
						/

- Click on the UPLOAD (START) button - During the update, do not move away with the watch from the mobile phone and, if possible, try to keep the phone screen active by occasionally clicking on the phone screen to avoid closing the application during the transfer. Wait for the update to complete - about 2-3 minutes.

14:19 🖬 🧃	ଦ ⊻ ା ଛିଂଶା ଘି2	6 %	14:19 🖪 🧃	¢ ⊻	՝ ≭ ଲି"ոI ն	26 %
← HID OTA	SETTIN	IGS	← HI	D A Over BLE	SETTI	NGS
	UPLOAD			STOP		
		-	ota proces	sing		29%
			sending file 1/	′1		20.0
Device	HIGET F60 / AB:2A:21:B0:0C:37	>				
Work Mode	Normal Mode	>	Device	HIGET F60 / AB:	2A:21:B0:0C:37	>
	app_MP_unknown#_1.0.4.0_ec009		Work Mode		Normal Mode	>
File Path	ca2-bba5e702b9d4c464a4a4b5cf2 75bb59e.bin	>	File Path	app_MP_unknown# ca2-bba5e702b9d4	1.0.4.0_ec009 c464a4a4b5cf2 75bb59e.bin	>
					•	
					-	

- In case of the error message "low image version", click on SETTINGS and turn off the Image Version check in the Image version section in the DFU CONFIGURE tab. Try again.

		N 011 00 00	_	← Settings
÷	13:42 • • • • •	SETTIN	GS	DFU DFU GATT
	OTA OVER BLE			Battery
		`	7	Battery Check Low Battery Warning
			-	Low Battery Threshold 30%
				Image Version
Device	HIGET F2X-BC1 / AD:2A	:21:AF:DB:C1	>	Image Version Check Low Version Warning
Work Mod	le	Normal Mode	>	Version Check Mode
File Path	low ir	mage version	>	STRICT
				DFU Configure

c) Update of dials – ONLY FOR F20 a F25

- Click on the **Device** item and in the list of available Devices by name (H may appear as the first letter) find your device type and verify that the MAC address also fits (you can find the MAC address in the watch in the Settings menu).

14:19 🖬 🧃 🗘	⊻	≭ 😤 [®] all 🛙 26 %	12:26 🧃
		SETTINGS	← Scanne
			Bondeded Devices
			ElePods 41:42:60:5E:6D:8F
			Parrot CK3100 00:12:1C:24:9E:A7
			SONY:GTK-X1BT D8:5D:E2:77:37:BC
9		No Device 📏	Available Devices
lode		>	HiGET F2X-C1D A5:2A:21:B0:0C:1D
h		No File 📏	FIT F3 F1:68:20:09:12:12
			HIGET F60 AB:2A:21:B0:1D:AA
			H027T_T_E07 AC:2A:21:B0:9E:07
			FIT F3 FF:BE:6E:F2:D4:BE
			FIT F3 CF:63:56:63:61:A1
			HIGET F30 AE:2A:21:AF:93:2C
			X1 C0:0D:95:72:ED:F0
			iGET F4 EA:72:DD:40:93:1D
\triangleleft	Ô		HUAWEI WATCH GT-28 F4:BF:80:88:42:84

- Work Mode set to Silent mode.
- File Path select the folder where you unzipped the downloaded ZIP archive and <u>select the file that</u> <u>contains:</u> the 026_6_04_20200519180938_MP-b08aadfa3a33d7f24d87d376198525d4.bin. Again, select the file as described above.

14:19 🖬 🧃 🗘 🗹	≭ ଲି"սI 🛙 26 %
← HID OTA Over BLE	SETTINGS
UPLOA	D
Device HiGET F2X-1D6 /	AB:2A:21:80:0C:37 >
Work Mode	Silent Mode >
File Path	No File 📏

- Click on the UPLOAD (START) button - During the update, do not move away with the watch from the mobile phone and, if possible, try to keep the phone screen active by occasionally clicking on the phone screen to avoid closing the application during the transfer. Wait for the update to complete - about 2-3 minutes.



When the update is complete (reaching 100%), go back to the home page and exit the application.

And you have DONE. The update does not necessarily take place in both steps, it is possible that the update will be released only on the UI or only on the FW watch itself.